



SD Series User Manual

Kerchan Technology Co., Ltd

For better shopping experience



Indexes

01	● Precautions	2-3
02	● Product Description	3-4
03	● Installation Steps	4
04	● Product Specification	5
05	● Function Introduction	6-7
06	● Malfunction Analysis	7
07	● Remote Control	8
08	● After sales	9



Dear Customers:

For better use of the product, please read this manual carefully, and keep it well for future reference.

01

Precautions

- 1.1 The descriptions of the advertising player in this manual are all illustrations, which may be different from the actual product. The final product is subject to our final product. Please understand the inconvenience caused to you, thank you!
- 1.2 During the installation and use of the product, the electrical safety regulations of the country and use area must be strictly abided by;
- 1.3 The power switch for advertising display should be kept away from children to prevent children from touching the power supply to prevent the risk of electric shock;
- 1.4 The power supply of the advertising player must be reliable and grounded correctly;
- 1.5 The power plug should be fully inserted into the socket to prevent leakage;
- 1.6 Do not disassemble or repair the player privately to prevent electric shock or other dangers;
- 1.7 The product is not waterproofed, do not expose it to rain, do not soak it in water, and do not install it in an outdoor environment;
- 1.8 Avoid harsh or extreme environments such as extreme high temperature (or low temperature), high humidity, vibration, radiation, chemical corrosion, etc;
- 1.9 Do not place the machine near a radiator or other heat source, so as not to affect the life of the machine;
- 1.10 When cleaning the advertising player, please unplug the power cord first to ensure that the player has been cut off;
- 1.11 When cleaning the LCD screen, do not use the sprayer directly to avoid damage to the screen;



1.12 If the product does not work normally, please contact the after-sales service personnel, and do not disassemble or modify the product in any way. We are not responsible for any problems caused by unauthorized modification or maintenance.


02

Product Description

2.1 Product Appearance




2.2 Interfaces



1	DC IN	12V DC input
2	USB 2.0	2.0 transport data interface
3	USB OTG	Upgrade firmware
4	SD	External Storage
5	HDMI OUT	Customize-able
6	Earphones	Audio amplifier output,8/2X10W
7	UBOOT	Upgrade the KEYPAD



2.3 Wiring diagram



03

Installation Steps

NOTE:

The LCD advertising screen is fragile. Please do not touch the touch panel and place it on the foam before the advertising screen is installed. (The following installation method only works for models below 21.5 inches, screens larger than 21.5 inches should be confirmed according to the actual situation)

- 3.1 Use 4 of 3.5mm self-tapping screws to fix the N2 bracket female seat to the display rack;
- 3.2 Fix the N2 bracket male seat to the back of the screen with 4 of M4*5mm screws;
- 3.3 Hang the screen directly on the wall of the display rack;



04

Product Specification

Product Series	SD Series	
Power Supply	100-230V AC 50/60HZ	
Screen	Size	10.1inch, 13.3inch, 15.6inch, 18.5inch, 21.5inch.
	Resolution	1920*1080/1366*768/1280*800
	Touch Screen	Not Support <input type="checkbox"/> Support <input checked="" type="checkbox"/>
Main board	CPU	A83T
	RAM	1G
	ROM	8G
	External storage	Up to 64GB SD card can be connected
General parameters	Installation Way	Wall Mount
	Working Humidity	5%~85%
	Working Temperature	-20℃~40℃
	Storage Temperature	-20℃~60℃
	Accessories	Screen* 1; Warranty Card* 1; Certificate * 1; Desiccant*1; Remote Controller*1 User Manual*



05

Function Introduction

5.1 How to set up the player?

5.1.1 Connect the screen with 100-230V AC power, it will start within 30s;

5.1.2 Brightness Setting: Settings-Display-Brightness level;

5.1.3 Sound Setting: Settings-Sound;

5.1.4 Language Settings: System-Languages & input;

5.1.5 Firmware Info: Settings-System-About tablet-Build number.

5.2 Switch On/Off Settings


5.2.1 Open K-Smart APP;

5.2.2 K-Smart Setting>Schedule ON/OFF setting;

L-

5.2.3 Default - Set the time to automatically turn on/off every day;

5.2.4 Can also set the on/off time every day according to the cycle;





5.3 How to copy video?

- 5.3.1 Create a new “adplayer” folder in the root directory of the U disk/SD card, create a folder “0” in the “adplayer” folder, and place video files into folder 0;
- 5.3.2 Run “K-smart” from the android menu, find K-Smart Settings/Media Player, and click Start K-Smart to enter the Media player;
- 5.3.3 In the Media player playing page, insert the U disk/SD card into the player, and the advertising player will automatically copy the video to the player's memory.

Remarks:

1. When the player is copying video, don't operate the player to prevent unsuccessful copying;
2. After copying the video, unplug the U disk/SD card, otherwise the player will restart the copy process again;
3. Please use Windows system computers for video copy instead of ios system;
4. Please use a brand new or clean USB to avoid playing troubles due to different files.

06


Malfuction Analysis

- 6.1 Black screen: Please check whether the power cord is in poor contact, falls off or is loose;
- 6.2 No sound but only image after power on: Please check whether the volume is the minimum or the mute switch is turned on;
- 6.3 Unsupported video: Please check whether it supports the current file format. If your file format is not supported, please Google and find a software to convert your file to our recommended format AVI or MP4;
- 6.4 Unable to copy the video: Please check whether the U disk or SD card is damaged, or whether there is a problem with the creation of the root folder.



07

Remote Control



	Power		Right
	Mouse Mode		Volume+
	Launcher		Volume-
	Up		Down
	OK		Back
	Left		



08

After sales

- 8.1 Please keep the warranty card as a proof of maintenance.
- 8.2 This product is guaranteed for 1 year from the date of purchase.
- 8.3 During the warranty period, under normal use and maintenance the player itself fails. After verification, the troubleshooting company will provide free repairs and replacement parts.
- 8.4 Warranty services will not be provided for situations where the warranty card and valid proof of purchase are unavailable, or for product malfunctions and damages caused by user misuse, external force, self-repair attempts by the user, natural disasters, or any other unforeseeable circumstances beyond our control.
- 8.5 The company reserves the right to modify and interpret all content.